

normen 40

RC5-kodes kaart 1

Adresnummer

Adresnummer	Betekenis
0	TV 1
1	TV 2
2	TXT
3	uitbreidingen voor TV 1 en TV 2
4	LV
5	VCR 1
6	VCR 2
7	gereserveerd
8	SAT 1
9	uitbreidingen voor VCR 1 en VCR 2
10	SAT 2
11	gereserveerd
12	CD-VIDEO
13	gereserveerd
14	CD-PHOTO
15	gereserveerd
16	PREAMP 1
17	TUNER
18	REC 1
19	PREAMP 2
20	CD
21	COMBI
22	SAT
23	REC 2
24	gereserveerd
25	gereserveerd
26	CD-R
27	gereserveerd
28	gereserveerd
29	gereserveerd
30	gereserveerd
31	gereserveerd

televisietoestel 1
televisietoestel 2
dezelfde functies als TV 1
Teletekst

LaserVision-speler
video-recorder 1
video-recorder 2
dezelfde functies als VCR 1

satelliet-TV-ontvanger 1

satelliet-TV-ontvanger 2
dezelfde functies als SAT 1

Compact-Disc-Video-speler

Photo-CD-speler

audio-voorversterker 1
radio-ontvanger
analoge cassette-recorder
audio-voorversterker 2
dezelfde functies als PREAMP 1
Compact-Disc-speler
audio-rack of opname-apparaat
satelliet-audio-ontvanger
DCC-recorder
dezelfde functies als REC 1

beschrijfbare CD

gemeenschappelijke kommando's voor alle adressen

nr. betekenis

0	
1	1
2	2
3	3
4	4
5	5
6	6
7	7
8	8
9	9
16	volume +
17	volume -
18	brightness +
19	brightness -
22	bass +
23	bass -
24	treble +
25	treble -
26	balance right
27	balance left
63	system select
71	dim local display
77	linear function incr.
78	linear function decr.
80	step up
81	step down
82	menu on
83	menu off
84	disp. A/V syst. status
85	step left
86	step right
87	acknowledge
118	sub mode
119	options sub-mode
123	connect
124	disconnect

gemeenschappelijke kommando's voor video-apparatuur

adres 0, 1, 2, 3, 4, 5, 6, 8, 9, 10, 12, 14

nr. betekenis

20	color saturation +
21	color saturation -
88	PIP on/off (Pay TV channel + for system 3)
89	PIP shift (Pay TV channel - for system 3)
90	PIP/main swap (radio channel + for system 3)
91	strobe on/off (radio channel - for system 3)
92	multi strobe (date + for system 9)
93	main frozen (date - for system 9)
94	3/9 multi-scan (start time + for system 9)
95	PIP select (start time - for system 9)
96	mosaic/multi-PIP (rec. program + for system 9)
97	picture DNR (rec. program - for system 9)
98	main stored (alternate channel for system 9)
99	PIP strobe (stop time + for system 9)
100	recall main picture (stop time - for system 9)
101	PIP freeze
102	PIP step up (+)
103	PIP step down (-)

normen 41

RC5-kodes kaart 2

adres 4

nr.	betekenis
10	pict. no./time
11	chapter no.
12	standby
13	mute/de-mute
15	display
28	TSP/repeat once
29	TSP/repeat cont.
30	next
31	fast run rev.
32	entry
33	auto stop
34	slow run rev.
35	audio 1
36	audio 2
37	still reverse
38	speed +
39	speed -
40	slow run fwd.
41	still fwd.
42	fast run fwd.
43	search auto
44	scan rev.
45	close/open
46	scan fwd.
47	play rev./direction
48	pause
49	erase/correct
53	play
54	stop
56	external 1
57	external 2
58	clear memory
59	freeze segment
60	TXT/RF switch
62	CX (1,2,3)

adres 5, 6
(VCR 1,2)

nr.	betekenis
10	1/2/3 dig.
11	Select/VSP
12	standby
13	mute/de-mute
14	auto track/rf tune
28	today/OTT
29	timer prog.
30	rec. select
31	fast run rev.
32	step +
33	step -
34	slow run rev.
35	sound select
36	set clock/cal.
37	speed -
38	speed +
39	ITR
40	slow motion
41	still fwd.
42	fast run fwd.
43	search auto
44	scan rev.
45	close/open
46	scan fwd.
47	play rev./direction
48	pause
49	erase/correct
50	rewind
51	go to
52	wind
53	play
54	stop
55	record
70	AI pic. control
72	tracking +
73	tracking -

74	NICAM on/off
75	data stream start
76	data stream end
79	catalogue
104	timer prog. view
105	descramble on/off
106	skip commercial
107	red/adv. frame
108	Green/ 1/2 slow
109	yel./write TOC/VMI
110	cyan/date rec.
111	white/title rec.
112	VISS index next
113	VISS index previous
114	mark VISS
115	erase VISS
116	re-number VISS
117	blank search
120	auto repeat
121	ins./ch. search
122	Mon. SLD/ch. mem.
125	tuner/clock/monitor
128	tape select
127	child lock

adres 8, 10
(SAT 1,2)

nr.	betekenis
10	1/2/3 digits
11	ch./prog./freq.
12	standby
13	mute/de-mute
15	display
31	preset ant.
32	ch./prog. +
33	ch./prog. -
35	sound select
36	spatial stereo
37	audio mixed
39	antenna east
40	key A
46	TV-text/subtitle
47	guide
49	erase/correct
58	antenna west
59	preset antenna +
60	TXT sub-mode
62	ant. pos. standby
68	radio
73	retour
74	suite
79	next prog.
104	PIP size
107	red
108	green
109	yellow
110	cyan/vol. +
111	cyan/vol. -
112	mail box
113	envoi/pay TV
121	RF level ind.
122	Store op/close
127	parental access